

## DC-11201

### 2 Port - USB-KVM



#### Features

- Controls 2 PCs with one PS/2 or USB keyboard, one PS/2 or USB mouse, and one monitor.
- Supports Windows, Linux, Mac OS9/OSX, Sun Micro Solaris 8
- Supports USB to PS/2 keyboard and mouse conversion; eliminates the need for one set of keyboard and mouse cables.
- Supports 3 USB downstream ports (perfect for sharing USB scanners, USB printers, and USB CD-RW, etc.)
- Supports 3 types of switching: hardware push button, hot keys on PS/2 keyboard, and On-Screen-Display (OSD) utility software (for Windows).
- OSD utility indicates:
  - 1st Power status of connected computer(s).
  - 2nd Active host computer.
- Supports VGA resolutions up to 2048x1536.
- Plug and Play. No software driver is needed for PS/2 mouse and keyboard operation.

#### System requirements

- **Computer:** USB port, VGA port
- **Operating System:** Windows 98/98SE/2000/ME/XP, Mac OS9/OSX, Linux Kernel 2.3 or Later, Solaris 8.
- **VGA Cable:** 1 VGA female-to-male cable per computer
- **USB Cable:** 1 USB cable with one Type-A end and one Type-B end per computer

#### Connectors

- 1 Mini-DIN for PS/2 keyboard
- 1 Mini-DIN for PS/2 mouse
- 3 USB type A downstream connectors
- 2 USB type B upstream connectors
- 2 VGA input connectors (HDB15 Female), and one VGA output connector (HDB15 Female).

## **Specifications**

| <b>Model</b>                   | <b>DC-11201</b>   |
|--------------------------------|---|
| Complies USB revision          | USB 1.0, 1.1  |
| Working PC status LED          | 2   |
| USB upstream port              | 2   |
| VGA IN port                    | 2   |
| VGA OUT port                   | 1   |
| USB downstream port            | 3   |
| USB over current LED indicator | 3   |
| PS/2 keyboard port             | 1   |
| PS/2 mouse port                | 1   |
| Video resolution               | 2048 X 1536.  |
| Hardware supported             | PC/Mac/Sun Micro  |
| OS Supported                   | Windows 98/98SE/ME/2000/XP,<br>Mac OS9/OSX<br>Linux Kernel 2.3/above<br>Solaris 8/above |
| Active PC selection            | By push button<br>By hotkey (only in PS/2 keyboard)<br>By OSD utility( Windows )        |

## **Package Contents**

- 2 port USB KVM Switch
- CD with users manual, On-Screen-Display(OSD) utility

Art.Nr. **DC-11201** EAN-Nr. **4016032201076** USB-KVM Switch 1User, 2PCs